

DMX Signal Amplifier

- One DMX512 signal input, two DMX512 signal output.
- Dedicated to amplify, distribute and insulate the signal that comes from the lighting system equipment when it is connected to the bus of DMX512(or RS-485).
- Realize extending the signal transmission distance.
- Signals expansion output control, increase DMX (485) signal amplifier to distribute multi-channel control.
- Photo-electricity insulation between input and output terminals, output terminals among channels, so as to avoid the expensive equipment such as light, 485 communications equipment, DMX driver, precise digital lighting controller, being burnt by the possible high voltage which caused from the wrong wire connection and a broken equipment, also can avoid the signal interference between each DMX equipment.



CE RoHS emc LVD

Technical Parameters

Input and Output		Environment		Safety and EMC	
Input voltage	12-48VDC	Operation temperature	Ta: -30°C ~ +55°C	EMC standard (EMC)	EN IEC 55015:2019+A11:2020
Input current	0.5A Max.	Case temperature (Max.)	Tc: +65°C		EN 61547:2009
Input signal	DMX512	IP rating	IP20		EN IEC 61000-3-2:2019+A11:2021
Output signal	DMX512 x 2	Package			EN 61000-3-3:2013+A11:2019
Warranty		Size	L178 x W50 x H38mm	Safety standard(LVD)	EN 61347-1:2015+A1:2021
Warranty	5 years	Gross weight	0.125kg		EN 61347-2-13:2014+A1:2017
Protection	Reverse Polarity			Certification	CE,EMC,LVD

Mechanical Structures and Installations

