


Fade-in Fade-out Push+RF LED Dimmer

Model No.: 22799

5 fading speed/Step-less dimming/Push Dim/Wireless remote control/Multiple protection

Features

- Fade-in Fade-out LED dimmer with smooth fading effect for soft start and stop.
- The fading speed can be set via knob potentiometer, 1S, 3S, 5S, 10S, 20S selectable.
- Connect with self-resetting metal button or push switch to achieve on/off and 0-100% dimming function.
- Push input can accept either positive or negative trigger.
- Match with RF 2.4G single zone or multiple zone dimming remote control optional.
- Over-heat / Over-load / Short circuit protection, recover automatically.



FC CE RoHS EMC RED

Technical Parameters

Input and Output		Dimming data		Safety and EMC	
Input voltage	12-48VDC	Input signal	Push Dim + RF 2.4GHz	EMC standard (EMC)	ETSI EN 301 489-1 V2.2.3 ETSI EN 301 489-17 V3.2.4
Input current	8A	Control distance	30m(Barrier-free space)	Safety standard(LVD)	EN 62368-1:2020+A11:2020
Output voltage	12-48VDC	Dimming gray scale	4096 (2 ¹²) levels	Radio Equipment(RED)	ETSI EN 300 328 V2.2.2
Output current	1CH,8A	Dimming range	0-100%	Certification	CE,EMC,LVD,RED
Output power	96-384W	Dimming curve	Logarithmic	Package	
Output type	Constant voltage	PWM Frequency	2000Hz (default)	Size	L120 x W43 x H27mm
Environment		Warranty		Gross weight	0.053kg
Operation temperature	Ta: -20°C ~ +55°C	Warranty	5 years		
Case temperature (Max.)	Ta: +85°C				

Mechanical Structures and Installations

